

CUSTOMER SERVICE BULLETIN

Radio Shack® CUSTOMER SERVICE BULLETIN

400 Atrium—One Tandy Center, Fort Worth, Texas 76102

Bulletin No. 1565-1
Description Microfiles
Model Model I
Stock No. 26-1565 Version 1.0
Date July 14, 1980
Page 1 of 2

Problem

If a file contains more than 256 records and you delete any record, you cannot add records to that file again. One exception is if the record deleted is the last.

Solution

Follow the procedure below for all Microfiles programs:

Using two disk drives:

1. Place a system disk in drive 0. This disk must have BASIC.
(Microfiles does not)
2. At the "DOS READY" message type BASIC, and press <ENTER> for FILES? and MEMORY?
3. Type in this program:

```
10 INPUT"READY NEXT DISK";A$
20 OPEN"R",1,"FILES/VIR"
30 FIELD#1,48 AS X1$,1 AS F1$,148 AS X2$,1 AS F2$
40 GET1,15:LSET F1$=CHR$(4):PUT1,15
50 GET1,3:LSET F2$="6":PUT1,3
60 CLOSE:GOTO 10
```

4. SAVE"MICRO/FIX"
5. Run the program with the Microfiles program disk in drive 1.
6. You can change all copies of the "Microfiles" program by swapping to the next disk you wish to correct at the point where "READY NEXT DISK" is displayed. Then press <ENTER>. To stop press <BREAK> when this message is displayed.

CUSTOMER SERVICE BULLETIN

Subject Microfiles Bulletin # 1565-1 Page 2 Of 2

For one drive users:

1. Follow steps 1-4 above.
2. Swap disks so that the Microfiles program is now in.
3. Type RUN
4. Step 6 on page 1 now applies. After pressing <BREAK> you are ready to use the corrected copies of the program.