

CUSTOMER SERVICE BULLETIN

Radio Shack® CUSTOMER SERVICE BULLETIN

400 Atrium—One Tandy Center, Fort Worth, Texas 76102

Bulletin No.	4501-1
Description	General Ledger
Model	Model II
Stock No.	26-4501 Version 1.2
Date	April 8, 1981
Page 1 of	2

Problem

The batch total does not equal the Document Total after document printing. This problem can also occur during posting.

Solution

The problem is corrected by following the steps listed below.

1. Backup the diskette(s) and make the changes on the Backup copy of the program.
2. In BASIC load the program by typing LOAD"Txentry".
3. Make the following corrections:

CHANGES (Retype the line or refer to the Edit section of the owners manual)

Old Line: 1450 IFHI<LOTHEN1405ELSEFORI=0TONA-1:S#(I)=Z#:NEXT

New Line: 1450 IFHI<LOTHEN1405ELSEFORI=0TONA-1:S#(I)=Z#:NEXT :BT#=Z#

ADDITIONAL LINES (Type the line followed by an <ENTER>)

6345 IFIN#>0THENBT#=BT#+IN#

4. Type SAVE"Txentry" to save the changes in the program.
5. In BASIC load the next program by typing LOAD"Txpost".
6. Make the following corrections:

CUSTOMER SERVICE BULLETIN

Subject General Ledger Bulletin # 4501-1 **Page** 2 **Of** 2

CHANGES (Retype the line or refer to the Edit section of the owners manual)

Old Line: 420 FORJ=0TONA-1:S#(J)=Z#:NEXT:RETURN

New Line: 420 FORJ=0TONA-1:S#(J)=Z#:NEXT:BT#=Z#:RETURN

ADDITIONS (Type the line followed by an <ENTER>)

3345 IFIN#>0THENBT#=BT#+IN#

7. Type SAVE"Txpost" to save the changes in the program.
8. At TRSDOS Ready, make a backup copy of the corrected diskette.